

Алматы (7273)495-231
 Ангарск (3955)60-70-56
 Архангельск (8182)63-90-72
 Астрахань (8512)99-46-04
 Барнаул (3852)73-04-60
 Белгород (4722)40-23-64
 Благовещенск (4162)22-76-07
 Брянск (4832)59-03-52
 Владивосток (423)249-28-31
 Владикавказ (8672)28-90-48
 Владимир (4922) 49-43-18
 Волгоград (844)278-03-48
 Вологда (8172)26-41-59
 Воронеж (473)204-51-73
 Екатеринбург (343)384-55-89

Ижевск (3412)26-03-58
 Иваново (4932)77-34-06
 Иркутск (395)279-98-46
 Казань (843)206-01-48
 Калининград (4012)72-03-81
 Калуга (4842)92-23-67
 Кемерово (3842)65-04-62
 Киров (8332)68-02-04
 Коломна (4966)23-41-49
 Кострома (4942)77-07-48
 Краснодар (861)203-40-90
 Красноярск (391)204-63-61
 Курск (4712)77-13-04
 Курган (3522)50-90-47
 Липецк (4742)52-20-81

Магнитогорск (3519)55-03-13
 Москва (495)268-04-70
 Мурманск (8152)59-64-93
 Набережные Челны (8552)20-53-41
 Нижний Новгород (831)429-08-12
 Новокузнецк (3843)20-46-81
 Ноябрьск (3496)41-32-12
 Новосибирск (383)227-86-73
 Омск (3812)21-46-40
 Орел (4862)44-53-42
 Оренбург (3532)37-68-04
 Пенза (8412)22-31-16
 Петрозаводск (8142)55-98-37
 Псков (8112)59-10-37
 Пермь (342)205-81-47

Ростов-на-Дону (863)308-18-15
 Рязань (4912)46-61-64
 Самара (846)206-03-16
 Саранск (8342)22-96-24
 Санкт-Петербург (812)309-46-40
 Саратов (845)249-38-78
 Севастополь (8692)22-31-93
 Симферополь (3652)67-13-56
 Смоленск (4812)29-41-54
 Сочи (862)225-72-31
 Ставрополь (8652)20-65-13
 Сыктывкар (8212)25-95-17
 Сургут (3462)77-98-35
 Тамбов (4752)50-40-97
 Тверь (4822)63-31-35

Тольяти (8482)63-91-07
 Томск (3822)98-41-53
 Тула (4872)33-79-87
 Тюмень (3452)66-21-18
 Улан-Удэ (3012)59-97-51
 Ульяновск (8422)24-23-59
 Уфа (347)229-48-12
 Хабаровск (4212)92-98-04
 Чебоксары (8352)28-53-07
 Челябинск (351)202-03-61
 Череповец (8202)49-02-64
 Чита (3022)38-34-83
 Якутск (4112)23-90-97
 Ярославль (4852)69-52-93

Киргизия (996)312-96-26-47

Россия (495)268-04-70

Казахстан (772)734-952-31

<https://exotek.nt-rt.ru> || exox@nt-rt.ru

Шумомер SL-8050-IL

APPLICATIONS & FEATURES

This Sound Level Meter is designed to be used in noise project; quality control; illness prevention and cure and all kinds of environmental sounds measurement. It is applied to the sound measurement at factory; school; office; traffic access and household, etc.

- This unit confirms to the IEC61672-1 CLASS2 for Sound Level Meters.
- MAX & MIN measurements
- Over range display
- Under range display
- dBA & dBC Weighting
- FAST & SLOW response
- Analog AC/DC outputs for connection to frequency analyzer or X-Y shaft recorder

TECHNICAL SPECIFICATION	SL-8050IL
Standard applied:	IEC61672 -1 CLASS2
Accuracy:	+1.4dB
Frequency range:	31.5HZ ~ 8KHZ
Dynamic range:	50dB
Level ranges:	LO 30dB~80dB
Med	50dB~100dB
Hi	80dB~130dB
Auto	30dB~130dB
Frequency weighting:	dBA/dBC
Time weighting:	FAST (125ms), SLOW (1s)
Microphone:	1/2 inch electret condenser microphone
Display: 4	digits LCD display with a resolution of 0.1dB
Display Update:	2 times/sec.
MAX hold:	Hold the Maximum reading
MIN hold:	Hold the Minimum reading
HOLD:	Hold the readings
Alarm function:	“OVER”is when input is more than upper limit of range. “UNDER”is when input is less than upper limit of range.
Analog output:	AC/DC outputs from earphone outlet AC=1 V rms DC=10mV/dB
Data output:	USB data traffic
Auto power off:	Meter automatically shuts down after approx. 15 minutes of inactivity.
Power supply:	One 9V battery, 006P or NEDA1604 or IEC 6F22
Power life:	About 30hours
Operation temperature and humidity:	0 C~40C ,10% RH~90% RH
Dimension	: 278 (L) x 76 (W) x 50(H) mm
Weight	: 350g



Complete with following accessories:
 : Instruction manual, battery, screwdriver, 3.5mm earphone plug, windscreen/ huffcover, software, USB cable, tripod and DC 9V power supply.

